



Backup 4 Switch PS 4000N

Technical Data Sheet

Product:	Backup 4 Switch PS 4000N manual Backup Switch, DMX and Ethernet.
Configuration:	High quality anodized aluminium desk housing. Big switcher for manual switching of 2 x 4 DMX 5-pin XLR inputs and 2 x Ethernet inputs to 4 x DMX 5-pin XLR outputs and 1 x Ethernet output. Ideally for switching between main and backup console. Live switching of DMX signals without any lagging. Passive device, no electrical power is needed. RDM compatibility.
Connectivity:	Full Boar 4, Main and Backup console (or similar DMX and Ethernet consoles and devices) for switching up to four DMX Universes and one Ethernet port.
Functions:	Switching between Main and Backup Systems, DMX and Ethernet.
Circuit Points:	2 x 4 x DMX 5-pin XLR input on the side 1 x 4 x DMX 5-pin XLR output on the back 2 x 1 x LAN 1000BaseTX GigaBit Neutrik Ethercon input on the side 1 x 1 x LAN 1000BaseTx GigaBit Neutrik Ethercon output on the back
Compliances:	CE, CETL, ETL
Dimensions and weight:	23.5 x 5.5 x 23.5 cm (w x h x d), 2.0 kg (unpacked)
Order numbers:	15.5915 Backup 4 Switch PS 4000N 80.1102 DMX 5-pin patch cable, 0.3m

The delivery is carried out without patch cables.
24 months world wide warranty.

All rights reserved. Errors, literal mistakes and technical changes reserved.
Named brands are the property of their respective company.

© 2012 Arcus Licht- und Präsentationstechnik GmbH



Arcus Licht- und Präsentationstechnik GmbH
Obermeiers Feld 2 - 4, D-33104 Paderborn, Germany
Phone: +49 (0) 5254 93069 0 · Fax: +49 (0) 5254 93069 29

Mail: info@arcus-lighting.com
Web: <http://www.arcus-lighting.com>
Web: <http://www.hog4.de>