



# Backup 4 Switch RS 8000N

## Technical Data Sheet

<b>Product:</b>	Backup 4 Switch RS 8000N manual Backup Switch, DMX and Ethernet.
<b>Configuration:</b>	High quality anodized 2U rackmount unit. Big switcher for manual switching of 2 x 8 DMX 5-pin XLR inputs and 2 x Ethernet inputs to 8 x DMX 5-pin XLR outputs and 1 x Ethernet output. Ideally for switching between main and backup console. Live switching of DMX signals without any lagging. Passive device, no electrical power is needed. RDM compatibility.
<b>Connectivity:</b>	DP 8000 DMX Processor, Main and Backup System (or similar DMX and Ethernet consoles or devices) for switching up to eight DMX Universes and one Ethernet port.
<b>Functions:</b>	Switching between Main and Backup Systems, DMX and Ethernet.
<b>Circuit Points:</b>	2 x 8 x DMX 5-pin XLR input on the front 1 x 8 x DMX 5-pin XLR output on the back 2 x 1 x LAN 1000BaseTX GigaBit Neutrik Ethercon input on the back 1 x 1 x LAN 1000BaseTx GigaBit Neutrik Ethercon output on the back
<b>Compliances:</b>	CE, CETL, ETL
<b>Dimensions and weight:</b>	48.3 x 9.0 x 25.5 cm (w x h x d), 2.8 kg (unpacked) 67.0 x 23.0 x 44.0 cm (w x h x d), 4.4 kg (packed)
<b>Order numbers:</b>	15.5990 Backup 4 Switch RS 8000N 80.1102 DMX 5-pin patch cable, 0.3m

The delivery is carried out without patch cables.  
24 months world wide warranty.

All rights reserved. Errors, literal mistakes and technical changes reserved.  
Named brands are the property of their respective company.

© 2012 Arcus Licht- und Präsentationstechnik GmbH



Arcus Licht- und Präsentationstechnik GmbH  
Obermeiers Feld 2 - 4, D-33104 Paderborn, Germany  
Phone: +49 (0) 5254 93069 0 · Fax: +49 (0) 5254 93069 29

Mail: [info@arcus-lighting.com](mailto:info@arcus-lighting.com)  
Web: <http://www.arcus-lighting.com>  
Web: <http://www.hog4.de>