

Nano Hog 4 Controller

Technical Data Sheet

Product:	Nano Hog 4 Controller (together with Hog 4 PC Software for Microsoft Windows XP, Windows Vista oder Windows 7) for controlling automated luminaires, dimmer and multimedia controllers.
Manufacturer:	High End Systems, Inc., Austin, Texas 78758 USA.
Configuration:	Ten LED fitted playback controller (Fader, Choose, Go, Pause, Back & Flash). Programmingsection including four parameter wheels, 12 User Keys, number pad and keys for parameters, groups, timing and effects. Two dimmable LED-Desklights. Two expansion slots for optional DMX Expansion Cards and/or MIDI/LTC Expansion Cards.
Connectivity:	Up to 2 \times Expansion Card DMX, each with 4 \times DMX 5-pin XLR outputs, isolated
	Up to 2 \times Expansion Card MIDI/LTC, each with 3 \times DIN 5-pin MIDI In/Out/Thru (MIDI-Timecode/MIDI-Showcontrol) and 1 \times LTC 3-pin XLR Timecode input
Circuit Points:	2 × Widget Expansion Slots on the back 2 × USB on the back 1 × LED desk light connector on the back 1 × Power Connector for 12V external power supply on the back
Electrical requirements:	Mains in 90 - 250VAC, 50/60Hz (external power supply)
Compliances:	CE, CETL, ETL.
Dimensions and weight:	$67.8 \times 9.0 \times 34.5$ cm (w × h × d) 8,2 kg (unpacked)
Order numbers:	15.3400 Nano Hog 4 Controller 15.4450 Nano Hog 4 Controller Case 15.4250 Nano Hog 4 Expansion Card 4 × DMX
	15.4260 Nano Hog 4 Expansion Card MIDI/LTC

The delivery is carried out without road case, operational, incl. 1 x LED desklight, dustcover, external power supply.

12 months world wide warranty.

All rights reserved. Errors, literal mistakes and technical changes reserved. Named brands are the property of their respective company.

© 2012 Arcus Licht- und Präsentationstechnik GmbH



Arcus Licht- und Präsentationstechnik GmbH Obermeiers Feld 2 - 4, D-33104 Paderborn, Germany Phone: +49 (0) 5254 93069 0 · Fax: +49 (0) 5254 93069 29 Mail: info@arcus-lighting.com Web: http://www.arcus-lighting.com

Web: http://www.hog4.de